

Publication CIE 162:2004

**Chromatic Adaptation Under Mixed Illumination Condition
When Comparing Softcopy and Hardcopy Images****CORRIGENDUM 1**

Page 12

6.2 Calculations*Replace the equation (6.13), by the following:*

$$Y_{adp} = \left\{ R_{adp} \cdot Y_{n(CRT)}^{1/3} + (1 - R_{adp}) \cdot Y_{ambiant}^{1/3} \right\}^3 \quad (6.13)$$

Page 15

ANNEX: WORKED EXAMPLE*Replace the existing Annex, by the following:*

ANNEX: WORKED EXAMPLE

$X_{(CRT)}$	$Y_{(CRT)}$	$Z_{(CRT)}$	38.00	40.00	59.00	Input Data (cd/m ²)
$X_{n(CRT)}$	$Y_{n(CRT)}$	$Z_{n(CRT)}$	76.23	80.00	118.63	Input Condition (cd/m ²)
$X_{ambient}$	$Y_{ambient}$	$Z_{ambient}$	161.53	160.00	102.01	Input Condition (cd/m ²)
$X'_{(CRT)}$	$Y'_{(CRT)}$	$Z'_{(CRT)}$	0.475	0.500	0.738	eq.6.5
$X'_{n(CRT)}$	$Y'_{n(CRT)}$	$Z'_{n(CRT)}$	0.953	1.000	1.483	eq.6.6
$X'_{ambient}$	$Y'_{ambient}$	$Z'_{ambient}$	1.010	1.000	0.638	eq.6.7
$L_{(CRT)}$	$M_{(CRT)}$	$S_{(CRT)}$	0.443	0.519	0.733	eq.6.1
$L_{n(CRT)}$	$M_{n(CRT)}$	$S_{n(CRT)}$	0.887	1.036	1.475	eq.6.2
$L_{ambient}$	$M_{ambient}$	$S_{ambient}$	1.066	0.991	0.644	eq.6.3
F			1.0			Input Condition
L_A			16.00			Input Condition
D			0.852			eq.6.9
$L'_{(CRT)}$	$M'_{(CRT)}$	$S'_{(CRT)}$	0.491	0.504	0.532	eq.6.8
$L'_{n(CRT)}$	$M'_{n(CRT)}$	$S'_{n(CRT)}$	0.902	1.031	1.378	eq.6.11
R_{adp}			0.6			Input Condition
Y_{adp}			107.64			eq.6.13 (cd/m ²)
$L''_{n(CRT)}$	$M''_{n(CRT)}$	$S''_{n(CRT)}$	0.977	1.012	1.043	eq.6.12
L_S	M_S	S_S	0.454	0.513	0.703	eq.6.15